



**Connect GOLD to  
Swegon INSIDE Cloud**



# Which units are **INSIDE** Ready?

## **GOLD units produced week 22, 2023 or later**

- Software version 2.41 or later
- Certificate installed in production on units produced from week 22, 2023

## **Retrofit functionality**

- Software version 2.42 or later
- GOLD version E / F




# How to connect GOLD units

# Going online with GOLD


## 1. Ethernet Connection

Connect one end of the network cable to the facility's existing network and the other end of the cable to the AHU (IQLogic).




## 2. Cellular Connection

Use a 4G router with SIM-card, specially developed for this purpose.




# Activate Swegon INSIDE in HMI/Web



Go to “Communication”


Make sure that the following fields are filled in correctly:

- IP address, Net mask, Default gateway, Primary DNS
- The product’s Serial number



# Create an account

- Go to [Swegon's webpage](#)
  - Software → Connected products
- 1 Request access to the INSIDE Portal
- 2 Fill in the form and click Submit
  - Wait for the invitation email to the INSIDE Portal.




The image shows the 'Request access to INSIDE Portal' form. It includes a title 'Get started!', a sub-header '1. Request access to INSIDE Portal', and instructions: 'Enter details below to request a login.' and 'If you already have an account and wish to add a new product or building, please contact digitalservices@swegon.com'. The form is divided into 'Account information' and 'Building and product information' sections. The 'Account information' section has fields for 'Email (will be used as username)\*', 'First name\*', and 'Last name\*'. The 'Building and product information' section has a 'Choose product\*' dropdown menu, 'Serial number of product\*', 'Building name\*', 'Building address\*', 'City\*', and 'Country\*' fields. A 'SUBMIT' button is at the bottom right. A green arrow with the number '2' points to the 'SUBMIT' button.

# 1. Log in to INSIDE Portal

## Swegon INSIDE Portal

- <https://inside.swegon.com>



The screenshot shows the Swegon INSIDE Portal login interface. On the left, there is a decorative graphic of overlapping semi-circles in various colors (orange, yellow, green, blue, purple) and the text "Feel good **inside**". On the right, the login form is titled "Welcome to Swegon INSIDE". Below the title, there is a paragraph of text: "You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account." The form includes fields for "Email" and "Password", a "Remember Login" checkbox, and a "Forgot your password?" link. A green "Log in" button is positioned below these fields. Below the button, there is an "OR" separator and a "Login as internal provider" button with a small green leaf icon. At the bottom, there is a "Don't have an account?" section with a "Sign up here" link.

Feel good **inside**

**Welcome to Swegon INSIDE**


You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account.

Email  
Password

Remember Login    [Forgot your password?](#)

**Log in**

OR

 Login as internal provider

**Don't have an account?**  
[Sign up here](#)

## 2. Go to building page

The screenshot displays the Swegon user interface for an organization. The breadcrumb navigation at the top reads "Home > Organisations > Company Name". A "GO BACK" button is on the left, and an "EDIT ORGANISATION" button is on the right. The main heading is "Company Name".


The "Buildings" section is highlighted with a red circle. It contains a search bar labeled "Search for building name" with a magnifying glass icon. Below the search bar is a table with the following data:

Name	City	Country	Number of products	Role
Head Office	Stockholm	Sweden	0	Organisation Admin

The "Head Office" entry is also highlighted with a red circle. At the bottom of the table, it says "Rows per page: 100" and "1-1 of 1". Below the table are sections for "Organisation administrators" and "App users", both with expandable arrows. A user profile icon with the initials "PA" is visible in the bottom left corner.



### 3. Press "Claim product"



Home > Buildings > Head Office

[← GO BACK](#)

## Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number)

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
Sorry, no matching records found						

Rows per page: 100 ▾ 0-0 of 0 < >

### Building administrators

PA

The screenshot shows a web interface for a building management system. The main content area displays the name 'Head Office' and its location 'Stockholm, Sweden' along with latitude and longitude coordinates. Below this is a 'Products' section with a search bar and a table. The table has columns for Name, Product type, Building, Serial number, Software version, Active alarm, and Connected. A message 'Sorry, no matching records found' is displayed in the table. A green button labeled '+ CLAIM PRODUCT' is circled in red in the top right corner of the products section. The interface also includes a sidebar with navigation icons and a bottom status bar with a 'PA' indicator.

4. Type in the product's serial number and press right outside the text box to confirm. After clicking outside the text box, there is the possibility to add additional serial numbers the same way.

The screenshot displays the Swegon web interface for a building named 'Head Office' in Stockholm, Sweden. The interface includes a navigation menu on the left, a breadcrumb trail (Home > Buildings > Head Office), and a 'GO BACK' button. The main content area shows the building name, location, and coordinates. Below this, there is a 'Products' section with a search bar and a table. A modal dialog box titled 'Claim product(s)' is open, containing a text input field for the serial number, a 'SUBMIT' button, and a '+ CLAIM PRODUCT' button. The dialog box also includes instructions on how to find the serial number on the product's internal website.

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden

Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number) 🔍

Name ↑	Product type	Software version	Active alarm	Connected
Sorry, no matching records found				

Building administrators

#### Claim product(s)

Once you have activated INSIDE on your INSIDE Ready product, you can claim the product to connect it to your building and start benefiting from our digital services.

The serial number can be found on the product's internal website under the 'Communication' tab


✓ SUBMIT

+ CLAIM PRODUCT

Rows per page: 100 ▾ 0-0 of 0 < >

5. Before submitting you need to name your units. Then press submit.

If the product is already connected to INSIDE Cloud, you need to enter the MAC-address of the product to claim it.



## 6. Now you have successfully claimed your products.

Home > Buildings > Head Office

[← GO BACK](#)

### Head Office

Stockholm, Sweden

Latitude: 59.32576641998  
Longitude: 18.070390739956

#### Products

Search (name, serial number)  [+ CLAIM PRODUCT](#)

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >

#### Building administrators

PA

7. If your products are disconnected (as shown below), you need to check that Swegon INSIDE is activated on the product and that it has a valid certificate (INSIDE Ready).

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden  
 Latitude: 59.32576641998  
 Longitude: 18.070390739956

**Products**

Search (name, serial number)

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >

**Building administrators**


PA




**If your product doesn't have a valid certificate:**  
Here's how to make your product INSIDE Ready  
(Retrofit)

# Make sure you have SW 2.42 or later

## Retrofit




# Activate Swegon INSIDE in HMI/Web Retrofit



Go to “Communication”

Make sure that the following fields are filled in correctly:

- IP address, Net mask, Default gateway, Primary DNS
- The product’s Serial number





1. Go to your building and click on the product you want to make INSIDE Ready.

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number)

+ CLAIM PRODUCT


Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >


### Building administrators

PA

2. Press the button “MAKE INSIDE READY”.



### 3. Type in the product's MAC address and press submit.



Home > Organisations > Company Name > Building: Head Office > Product: GOLD1

← GO BACK

+ MAKE INSIDE READY EDIT NAME

# GOLD1

Not connected ●  
Software version: -  
Serial number: 1111111111

Reports


Active alarms

### Make INSIDE Ready

Making your product INSIDE Ready is the first step to benefit from Swegon's digital services. INSIDE Ready means that the product has the capability to securely connect and deliver data to the Swegon INSIDE Cloud. Read more and see the requirements [here](#)

✓ SUBMIT

3. Copy the ID and Activation code and paste it in the right text fields in your products HMI and press “Activate”.  
Now you have successfully connected your product!



For GOLD units you will find the text fields under “Communication”

4. When the products are connected and sharing data with INSIDE Cloud, the dots light up green.

The screenshot displays the Swegon INSIDE Cloud interface for the 'Head Office' in Stockholm, Sweden. The interface includes a navigation menu on the left, a breadcrumb trail (Home > Buildings > Head Office), and a 'GO BACK' button. The main content area shows the building name and location, along with its latitude and longitude. Below this is a 'Products' section with a search bar and a '+ CLAIM PRODUCT' button. A table lists two products, GOLD1 and GOLD2, both of which are connected, as indicated by green dots in the 'Connected' column. The table also shows columns for Name, Product type, Building, Serial number, Software version, and Active alarm. At the bottom, there is a 'Building administrators' section.

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●



# INSIDE Portal

Connecting GOLD units to the Swegon INSIDE cloud  
enables remote monitoring and digital services


# INSIDE Portal

– The hub for all connected Swegon products.

INSIDE Portal allows you to:

- Monitor key parameters
  - Status of air flow, pressure drop, temperatures etc.
  - Active alarms
- Generate and export energy reports
- Gain high level insights into the AHU performance
- Easily activate additional services that can increase the efficiency of your system
- Invite portal users to share insight and delegate level of access

INSIDE Portal is free of charge



# INSIDE Portal - Alarm subscriptions

Get alarm notifications to your email from connected units

Home > Alarm subscriptions

My alarm subscriptions

Search for any keyword

DELETE SELECTED EDIT SELECTED + ADD ALARM SUBSCRIPTION

<input type="checkbox"/>	Product name	Notify at (severity)	Building name	City	Country	Product type	Organisation
<input type="checkbox"/>	Kv Målet 1, Umeå	A B	Swegon Umeå	Umeå	Sweden	SuperWISE	Swegon
<input type="checkbox"/>	Åbyhøj GOLD	A B	Swegon Åbyhøj	Åbyhøj	Denmark	GOLD	Swegon Denmark
<input type="checkbox"/>	Zeta Sky Hi R7 (R32)	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	Titan Sky Hi R0 HP	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	GEYSER Sky R0 (R290)	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	Epsilon Sky Hi	A	Swegon Cantarana	Cantarana	Italy	BlueBox Epsilon SKY	Swegon
<input type="checkbox"/>	Boställsvägen 1 Örebro	A B T	Swegon Örebro	Örebro	Sweden	SuperWISE	Swegon
<input type="checkbox"/>	SWEGON BUREAU	A B T	Swegon France Lyon	Lyon	France	SuperWISE	Swegon
<input type="checkbox"/>	Zeta Rev	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	TA/FA 73	A B T	Swegon Kvånum	Kvånum	Sweden	GOLD	Swegon
<input type="checkbox"/>	OPEN SPACE	A	Swegon Cantarana	Cantarana	Italy	GOLD	Swegon

PA



# INSIDE Portal - Alarm subscriptions

Select which alerts you want to be notified of via email

The screenshot shows the 'Add alarm subscriptions' modal window. The table lists various alarm types and locations, each with checkboxes for selecting notification severity levels (A, B, T). The 'Notify at (severity)' column has a dropdown menu set to 'A'. The 'Product name' column has a dropdown menu set to 'A'. The 'Building name' column has a dropdown menu set to 'A'. The 'City' column has a dropdown menu set to 'A'. The 'Country' column has a dropdown menu set to 'A'. The 'Product type' column has a dropdown menu set to 'A'. The 'Organisation' column has a dropdown menu set to 'A'.

Product name	Notify at (severity)	Building name	City	Country	Product type	Organisation
Zeta Sky Hi R7 (R32)	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
Titan Sky Hi R0 HP	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
GEYSER Sky R0 (R290)	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
Epsilon Sky Hi	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
Zeta Rev	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
OPEN SPACE	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T					
Boställsvägen 1 Örebro	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Örebro	Örebro	Sweden	SuperWISE	Swegon
SWEGON BUREAU	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon France Lyon	Lyon	France	SuperWISE	Swegon
TA/FA 73	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Kvänum	Kvänum	Sweden	GOLD	Swegon
Äbyhøj GOLD	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Äbyhøj	Äbyhøj	Denmark	GOLD	Swegon Denmark
Kv Målet 1, Umeå	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Umeå	Umeå	Sweden	SuperWISE	Swegon
TA 12	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Gothenburg	Gothenburg	Sweden	GOLD	Swegon
GOLD 2005646491	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Sundsvall	Sundsvall	Sweden	GOLD	Swegon
Swegon - Brandby	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Brandby	Brandby	Denmark	SuperWISE	Swegon Denmark
Swegon Malmö	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Malmö	Malmö	Sweden	SuperWISE	Swegon
Swegon Goteborg	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Gothenburg	Gothenburg	Sweden	SuperWISE	Swegon
LB03 Luleå	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Luleå	Luleå	Sweden	GOLD	Swegon
GOLD Umeå	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Umeå	Umeå	Sweden	GOLD	Swegon
Norrkøping kontor	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> T	Swegon Norrkøping	Norrkøping	Sweden	SuperWISE	Swegon

# INSIDE Portal: Overview of connected units

Home > Buildings

Buildings

Name	City	Country	Number of products	Role
Swegon Åbyhøj	Åbyhøj	Denmark	1	Organisation Admin
Swegon Borås	Borås	Sweden	2	Organisation Admin
Swegon Brøndby	Brøndby	Denmark	2	Organisation Admin
Swegon Cantarana	Cantarana	Italy	6	Organisation Admin
Swegon France Lyon	Lyon	France	2	Organisation Admin
Swegon Gembloux	Gembloux	Belgium	1	Organisation Admin
Swegon Gothenburg	Gothenburg	Sweden	4	Organisation Admin
Swegon Kvänum	Kvänum	Sweden	4	Organisation Admin
Swegon Kvänum Testcenter	Kvänum	Sweden	2	Organisation Admin
Swegon Luleå	Luleå	Sweden	2	Organisation Admin
Swegon Malmö	Malmö	Sweden	1	Organisation Admin
Swegon Norrköping	Norrköping	Sweden	1	Organisation Admin
Swegon Örebro	Örebro	Sweden	1	Organisation Admin
Swegon Stockholm	Stockholm	Sweden	1	Organisation Admin
Swegon Sundsvall	Sundsvall	Sweden	1	Organisation Admin
Swegon Tomelilla	Tomelilla	Sweden	1	Organisation Admin
Swegon Umeå	Umeå	Sweden	2	Organisation Admin

Rows per page: 100 1-17 of 17

PA

Full overview of all buildings in your organisation

- Building name
- Building location
- Number of products

# INSIDE Portal: Overview of connected units



Home > buildings > Swegon Kvänum

← GO BACK

## Swegon Kvänum

Kvänum, Sweden  
Latitude: 58.2980300699508  
Longitude: 13.189557

### Products

Search (name, serial number) 🔍

Name	Product type	Building	Serial number	Software version	Active alarm	Connected
Kvänum Tellus, Casa	GOLD	Swegon Kvänum	G00403364	2.42		●
Swegon Kvänum	WISE	Swegon Kvänum	6V5M1U5CIUTPHT38WDXD	1.160.1		●
TA/FA 37	GOLD	Swegon Kvänum	G320716	2.42		●

Rows per page: 10 ▾ 1-3 of 3 < >

### Rooms

### Building administrators

FR

Full overview of the Swegon products in each building

- Location
- Software version
- Active alarms
- Status of connectivity

# INSIDE Portal: Monitor performance

← GO BACK EDIT NAME

## GOLD RXHC 12

Connected ●  
Software version: 2.42  
Serial number: 2006392391

### Information

**AHU status**

AHU status	Damper switch off delay
<b>Supply air</b>	
Supply air	15.9 °C
Supply air flow	803.0 l/s
Supply air fan power consumption	0.6 kW
Supply air duct pressure	112.5 Pa
<b>Supply filter</b>	
Supply air internal filter	106.7 Pa
Supply air internal filter alarm	0.0 Pa
<b>Extract air</b>	
Extract air	23.0 °C
Extract air flow	800.0 l/s
Extract air duct pressure	109.3 Pa
Extract air fan power consumption	0.5 kW
<b>Extract filter</b>	
Extract air internal filter	66.5 Pa

**Monitor:**

- Operation status
- Key parameters
- Energy data
- Alarms

*Live, in real time...*

Temperature  
 °C  
 °F

Pressure  
 Pa  
 psi  
 in.wc

Airflow  
 l/s  
 cfm  
 m³/s  
 m³/h

# INSIDE Portal: Monitor performance

Energy	
Cool power recovery	0.0 kW
Specific fan power	1.4 kW/m <sup>3</sup> /s
Temperature efficiency	0.0 %
Heat power recovery	0.0 kW
Temperature efficiency	0.0 %
Heat exchange motor energy consumption since unit installation	0.2 MWh
Heat energy consumption since unit installation	12.0 MWh
Total Heat Cool energy consumption since unit installation	16.1 MWh
Total energy recovery since unit installation	59.6 MWh
Total air fan energy consumption since unit installation	8.4 MWh
Supply air fan energy consumption	1.3 MWh
Heat energy recovery since unit installation	59.2 MWh
Supply air fan energy consumption since unit installation	4.2 MWh
Extract air fan energy consumption	1.2 MWh
Total AHU energy consumption since unit installation	8.6 MWh
Heat exchange motor power consumption	0.0 kW
Extract air fan energy consumption since unit installation	4.2 MWh
Cool energy recovery since unit installation	0.5 MWh
Total AHU energy consumption	2.6 MWh
Heat exchange motor energy consumption	0.0 MWh
Cool energy consumption since unit installation	4.1 MWh

Alarms	
Alarm priority A triggered	0
Alarm priority B triggered	0

Detailed information about active alarms

Alarms	
Name	Raised at
Info 98:7 Extract air air handling unit filter calibration not performed	2023-07-19 07:24
Info 98:5 Supply air air handling unit filter calibration not performed	2023-07-19 07:24

Rows per page: 100 1-2 of 2

# INSIDE Portal: Energy report



Home > buildings > Swegon Kvänum > Product: Kvänum Tellus, Casa

Connected ●  
Software version: 2.42  
Serial number: G00403364

Information

Reports

CREATE REPORT   DOWNLOAD REPORT ↓   DELETE REPORT(S)

<input type="checkbox"/>	Created	Status	From	To
<input checked="" type="checkbox"/>	2023-05-29 08:10	Completed	2023-05-01	2023-05-29
<input type="checkbox"/>	2023-05-10 07:54	Completed	2023-04-01	2023-05-02
<input type="checkbox"/>	2023-04-13 08:04	Completed	2023-03-17	2023-04-13
<input type="checkbox"/>	2023-04-11 13:48	Completed	2023-04-05	2023-04-10
<input type="checkbox"/>	2023-04-07 17:56	Completed	2023-03-16	2023-04-07
<input type="checkbox"/>	2023-03-27 10:17	Completed	2023-03-20	2023-03-27
<input type="checkbox"/>	2023-03-14 10:03	Completed	2023-03-06	2023-03-13

1 row selected

FR Uploads



Rows per page: 10   1-7 of 7

Quick and easy to generate energy reports of connected units

# Energy report


## Analyse performance

Generate energy reports using preferred time interval and detail level.



# INSIDE Portal: Log in

Log in to INSIDE Portal: <https://inside.swegon.com/>



The screenshot shows the Swegon INSIDE login page. On the left, there is a decorative graphic of overlapping semi-circles in various colors (orange, yellow, green, blue, purple) and the text "Feel good **inside**". On the right, the login form is titled "Welcome to Swegon INSIDE". Below the title, there is a paragraph of text: "You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account." The form includes an "Email" input field, a "Password" input field, a checkbox for "Remember Login", and a link for "Forgot your password?". A green "Log In" button is positioned below these fields. Below the button, there is an "OR" separator and a button labeled "Login as internal provider" with a small green leaf icon. At the bottom, there is a section titled "Don't have an account?" with a link "Sign up here".

Feel good **inside**

**Welcome to Swegon INSIDE**

You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account.


Email

Password

Remember Login    [Forgot your password?](#)

**Log In**

OR


 Login as internal provider

**Don't have an account?**


[Sign up here](#)



# Several ways to monitor GOLD



# Digital services



## INSIDE Director

Combination of BMS and EMS functionality for a complete building stock.

## INSIDE Analytics & Visualiser

Analysis and visualisation of the indoor climate.

## INSIDE Portal

Remote monitoring of the AHU's key parameters, active alarms and energy consumption.

**Swegon** 





Feel good **inside**